



## **HOWTO : Overall-Reset for all VIPA CPUs**

To delete all User Programm and Configuration Data from Ram Memory on any of the VIPA CPUs please follow these steps:

- 1.- Power On the CPU.
- 2.- After CPU started in RUN or STOP Mode hold down the RUN/STOP-Switch to MRES (completely down) for 3s at this position, the stop LED has to blink for 3 times slowly .
- 4.- Release the RUN/STOP-Switch.
- 5.- Hold the RUN/STOP-Switch again down for 1s (STOP LED blinks quickly)
- 6.- Release the RUN/STOP-Switch.

At this moment your CPU should be without user program and hardware config. Also flags, databases, timers and counters should be deleted.